

INVESTIGATION OF A MULTIDIMENSIONAL AUTOMATIC CONTROL SYSTEM WITH DELAYS AND CHAIN FORM STRUCTURE

Gintarė Leonaitė, Jonas Rimas

*Department of Applied Mathematics, Kaunas University of Technology
Studentų St. 50, LT-51368 Kaunas, Lithuania*

Abstract. The dynamics of the forced synchronization system with delays, composed of n ($n \in N$) oscillators joint into a chain, is studied. The investigation is based on the use of Jordan's form, eigenvalues and eigenvectors of the matrix, which describes the structure of the internal links of the system.

Keywords: synchronization system, differential equation, delayed argument.

1. Formulation of the problem

The automatic control systems are used in various processes of production and in the networks of transmitting and distributing of the information. Often the delays of the fed signals in such systems must be evaluated. Despite the great achievements in the area of projection and implementation of control systems, the works devoted to the exact analytical investigation of such systems are relevant [1-2]. In the present work, the exact theoretical investigation of the concrete linear multidimensional delay system is carried out.

Let us consider a multidimensional delay system described by the following matrix differential equation

$$Dx(t) = B_0x(t) + B_1x(t - \tau) + z(t); \quad (1)$$

here D is the generalized differential operator (applicable to generalized functions), $B_0 = \text{diag}(0, -\kappa, -\kappa, \dots, -\kappa)$, κ is the coefficient,

$$B_1 = \frac{\kappa}{2} B,$$

$$B = \begin{pmatrix} 0 & 0 & & & \\ 1 & 0 & 1 & & 0 \\ & 1 & 0 & 1 & \\ & & & \ddots & \\ 0 & & 1 & 0 & 1 \\ & & & & 2 & 0 \end{pmatrix} \quad (2)$$

is the n -th order matrix, $x(t) = (x_1(t), x_2(t), \dots, x_n(t))^T$ is the desired vector function (T denotes operation of transposition), $z(t)$ is the vector function, depending on the initial conditions, τ is the constant delay.

As an example of a control system described by the equation (1), the forced synchronization system of the communication network, composed of n oscillators joined into a chain, can be pointed out [1,2]. In this case, the symbol $x_i(t)$ ($i = \overline{1, n}$) in (1) stands for the phase of the i -th oscillator.

We will investigate the dynamics of the system.

2. Step responses matrix of the system

2.1. The solution of the matrix equation

We solve the matrix differential equation with delayed argument (1) by applying method of "steps". The interval $0 < t < +\infty$ is divided into subintervals. The lengths of these subintervals are equal to the delay τ . The differential equation (1) in each subinterval is solved separately. The solution, obtained in some subinterval is used as initial function, solving the equation in the next subinterval. Applying the Laplace transform, we write down the solution of the equation (1) as follows [2]:

$$x(t) \div \sum_{l=0}^L (A^{-1} B_1 e^{-l\tau})^l A^{-1} Z(p), \quad 0 < t < (L+1)\tau;$$

here $A = pE - B_0$, E is the identity matrix of the n -th order,

$$A^{-1} = \frac{1}{p + \kappa} \text{diag} \left(\frac{p + \kappa}{p}, 1, 1, \dots, 1 \right), \quad Z(p) \div z(p),$$

$Z(p)$ is the Laplace transform of the function $z(t)$ (sign \div links function with its Laplace transform), $L = 0, 1, 2, \dots$

$$u_{ij}(t) = \frac{1}{2n-2} \sum_{l=1}^L \frac{1}{2^l} q_{ij}(l) \frac{\kappa^l(t-l\tau)^l}{l!} \cdot e^{-\kappa(t-l\tau)} 1(t-l\tau), \quad i > 1, j > 1, 0 < t < (L+1)\tau,$$

$$v_{ij}(t) = \frac{1}{2n-2} \sum_{l=1}^L \frac{1}{2^l} q_{ij}(l) \left[1 - \sum_{v=0}^{l-1} \frac{\kappa^v(t-l\tau)^v}{v!} \cdot e^{-\kappa(t-l\tau)} \right] 1(t-l\tau), \quad i > 1, j = 1, 0 < t < (L+1)\tau,$$

$q_{ij}(l)$ is defined by (16); $1(t) = \begin{cases} 1, & \text{if } t \geq 0, \\ 0, & \text{if } t < 0, \end{cases}$ is the unit function.

Taking into account derived expressions, the step responses matrix for the forced synchronization system composed of n (n is an arbitrary even number) oscillators joined into a chain can be written down.

For example, if $n = 4$, we get

$$J = \begin{pmatrix} -\lambda_5 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & -\lambda_5 \end{pmatrix} = \begin{pmatrix} -a & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a \end{pmatrix},$$

$$B^l = \frac{1}{6}(q_{ij}) = \frac{1}{6} \begin{pmatrix} 0 & 0 & 0 & 0 \\ a_1 & a_2 & a_3 & a_2 \\ a_2 & a_3 & a_4 & a_3 \\ 2a_1 & 2a_2 & 2a_3 & 2a_2 \end{pmatrix},$$

$$a = \sqrt{3}, \quad a_1(l) = a^{l-1}(1 - (-1)^l), \\ a_2(l) = a^l(1 + (-1)^l), \quad a_3(l) = a^{l+1}(1 - (-1)^l), \\ a_4(l) = a^{l+2}(1 + (-1)^l), \quad l \in N, l \geq 2,$$

$$h(t) = (h_{ij}(t)) = \begin{pmatrix} 1(t) & 0 & 0 & 0 \\ h_1^{(1)} & \alpha + h_2 & h_3 & h_2 \\ h_2^{(1)} & h_3 & \alpha + h_4 & h_3 \\ 2h_1^{(1)} & 2h_2 & 2h_3 & \alpha + 2h_2 \end{pmatrix},$$

$$\alpha(t) = e^{-\kappa t} 1(t),$$

$$h_i(t) = \frac{1}{6} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \frac{\kappa^l(t-l\tau)^l}{l!} e^{-\kappa(t-l\tau)} 1(t-l\tau), \\ i = 2, 3, 4, \quad 0 < t < (L+1)\tau,$$

$$h_i^{(1)}(t) = \frac{1}{6} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \left[1 - \sum_{v=0}^{l-1} \frac{\kappa^v(t-l\tau)^v}{v!} \cdot e^{-\kappa(t-l\tau)} \right] 1(t-l\tau), \quad i = 1, 2, \quad 0 < t < (L+1)\tau.$$

If $n = 6$, we would obtain

$$J = \begin{pmatrix} -a & 0 & & & & \\ & -c & 0 & & 0 & \\ & & 0 & 1 & & \\ & & & 0 & 0 & \\ & 0 & & & c & 0 \\ & & & & & a \end{pmatrix},$$

$$B^l = \frac{1}{10}(q_{ij}) = \begin{pmatrix} 0 & 0 & 0 & 0 & 0 & 0 \\ a_1 & a_2 & a_6 & a_7 & a_8 & a_4 \\ a_2 & a_6 & a_9 & a_{10} & a_{11} & a_8 \\ a_3 & a_7 & a_{10} & a_{12} & a_{13} & a_{14} \\ a_4 & a_8 & a_{11} & a_{13} & a_{15} & a_{10} \\ 2a_5 & 2a_4 & 2a_8 & 2a_{14} & 2a_{10} & 2a_7 \end{pmatrix},$$

$$a_1(l) = (a^{l-1}d^2 + c^{l-1}b^2)(1 - (-1)^l),$$

$$a_2(l) = (a^l d^2 + c^l b^2)(1 + (-1)^l),$$

$$a_3(l) = (a^{l-1} + c^{l-1})(1 - (-1)^l),$$

$$a_4(l) = (a^l d - c^l b)(1 + (-1)^l),$$

$$a_5(l) = (a^{l-1}d - c^{l-1}b)(1 - (-1)^l),$$

$$a_6(l) = (a^{l+1}d^2 + c^{l+1}b^2)(1 - (-1)^l),$$

$$a_7(l) = (a^l + c^l)(1 + (-1)^l),$$

$$a_8(l) = (a^{l+1}d - c^{l+1}b)(1 - (-1)^l),$$

$$a_9(l) = (a^{l+2}d^2 + c^{l+2}b^2)(1 + (-1)^l),$$

$$a_{10}(l) = (a^{l+1} + c^{l+1})(1 - (-1)^l),$$

$$a_{11}(l) = (a^{l+2}d - c^{l+2}b)(1 + (-1)^l),$$

$$a_{12}(l) = (a^l b^2 + c^l d^2)(1 + (-1)^l),$$

$$a_{13}(l) = (a^{l+1}b - c^{l+1}d)(1 - (-1)^l),$$

$$a_{14}(l) = (a^l b - c^l d)(1 + (-1)^l),$$

$$a_{15}(l) = (a^{l+2} + c^{l+2})(1 + (-1)^l),$$

$$a = 2 \cos \frac{\pi}{10}, \quad c = 2 \cos \frac{3\pi}{10}, \quad b = 2 \cos \frac{\pi}{5},$$

$$d = 2 \cos \frac{2\pi}{5}, \quad l \in N, l \geq 2,$$

$$h(t) = (h_{ij}(t)) = \begin{pmatrix} 1(t) & 0 & 0 & 0 & 0 & 0 \\ h_1^{(1)} & \alpha + h_2 & h_6 & h_7 & h_8 & h_4 \\ h_2^{(1)} & h_6 & \alpha + h_9 & h_{10} & h_{11} & h_8 \\ h_3^{(1)} & h_7 & h_{10} & \alpha + h_{12} & h_{13} & h_{14} \\ h_4^{(1)} & h_8 & h_{11} & h_{13} & \alpha + h_{15} & h_{10} \\ 2h_5^{(1)} & 2h_4 & 2h_8 & 2h_{14} & 2h_{10} & \alpha + 2h_7 \end{pmatrix},$$

$$\alpha(t) = e^{-\kappa t} 1(t),$$

$$h_i(t) = \frac{1}{10} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \frac{\kappa^l (t-l\tau)^l}{l!} e^{-\kappa(t-l\tau)} 1(t-l\tau), \quad i = 2, 4, \overline{6, 15}, \quad 0 < t < (L+1)\tau,$$

$$h_i^{(1)}(t) = \frac{1}{10} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \left[1 - \sum_{v=0}^{l-1} \frac{\kappa^v (t-l\tau)^v}{v!} e^{-\kappa(t-l\tau)} \right] 1(t-l\tau), \quad i = \overline{1, 5}, \quad 0 < t < (L+1)\tau.$$

2.3.2. The order of the matrix B is an odd number

Substituting (19) into (4) and implementing necessary transformations, we find the step responses matrix of the system in the case where n is an odd number: $h(t) = (h_{ij}(t))$; here

$$h_{ij}(t) = \begin{cases} e^{-\kappa t} 1(t) + \overline{u_{ij}}(t), & \text{if } i = j > 1, \\ \overline{u_{ij}}(t), & \text{if } 1 < i \neq j > 1, \\ \overline{v_{ij}}(t), & \text{if } i > 1 \text{ and } j = 1, \end{cases} \quad (22)$$

$$\overline{u_{ij}}(t) = \frac{1}{2n-2} \sum_{l=1}^L \frac{1}{2^l} g_{ij}(l) \frac{\kappa^l (t-l\tau)^l}{l!} 1(t-l\tau),$$

$i > 1, j > 1, \quad 0 < t < (L+1)\tau,$

$$\overline{v_{ij}}(t) = \frac{1}{2n-2} \sum_{l=1}^L \frac{1}{2^l} g_{ij}(l) \left[1 - \sum_{v=0}^{l-1} \frac{\kappa^v (t-l\tau)^v}{v!} e^{-\kappa(t-l\tau)} \right] 1(t-l\tau), \quad i > 1, j = 1, \quad 0 < t < (L+1)\tau,$$

$g_{ij}(l)$ is defined by (20).

Taking into account derived expressions, the step responses matrix for the forced synchronization system composed of n (n is an arbitrary odd number) oscillators joined into a chain can be written down.

For example, if $n = 3$, we get $J = \text{diag}(-\lambda_3, 0, \lambda_3) = \text{diag}(-a, 0, a)$, $a = \sqrt{2}$,

$$B^l = \frac{1}{4} (q_{ij}) = \frac{1}{4} \begin{pmatrix} 0 & 0 & 0 \\ a_1 & a_2 & a_1 \\ a_2 & a_3 & a_2 \end{pmatrix},$$

$$a_1(l) = a^{l+1} (1 - (-1)^l), \quad a_2(l) = a^{l+2} (1 + (-1)^l),$$

$$a_3(l) = a^{l+3} (1 - (-1)^l), \quad l \in N,$$

$$h(t) = (h_{ij}(t)) = \begin{pmatrix} 1(t) & 0 & 0 \\ h_1^{(1)} & \alpha + h_2 & h_1 \\ h_2^{(1)} & h_3 & \alpha + h_2 \end{pmatrix},$$

$$\alpha(t) = e^{-\kappa t} 1(t),$$

$$h_i(t) = \frac{1}{4} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \frac{\kappa^l (t-l\tau)^l}{l!} e^{-\kappa(t-l\tau)} 1(t-l\tau)$$

$i = 1, 2, 3.$

$$h_i^{(1)}(t) = \frac{1}{4} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \left[1 - \sum_{v=0}^{l-1} \frac{\kappa^v (t-l\tau)^v}{v!} e^{-\kappa(t-l\tau)} \right] 1(t-l\tau), \quad i = 1, 2, \quad 0 < t < (L+1)\tau,$$

If $n = 5$, we would obtain $J = \text{diag}(-\lambda_5, -\lambda_4, 0, \lambda_4, \lambda_5) = \text{diag}(-a, -c, 0, c, a)$,
 $a = 2 \cos \frac{\pi}{8}$, $c = 2 \cos \frac{3\pi}{8}$,

$$B^l = \frac{1}{8} \begin{pmatrix} 0 & 0 & 0 & 0 & 0 \\ a_1 & a_2 & a_3 & a_4 & a_5 \\ a_2 & a_3 & a_6 & a_7 & a_4 \\ a_5 & a_4 & a_7 & a_8 & a_9 \\ 2a_{10} & 2a_5 & 2a_4 & 2a_9 & 2a_{11} \end{pmatrix},$$

$$a_1(l) = (a^{l-1} c^2 + c^{l-1} a^2) (1 - (-1)^l),$$

$$a_2(l) = (a^l c^2 + c^l a^2) (1 + (-1)^l),$$

$$a_3(l) = (a^{l+1} c^2 + c^{l+1} a^2) (1 - (-1)^l),$$

$$a_4(l) = (a^{l+1} c^2 - c^{l+1} a^2) (1 + (-1)^l),$$

$$a_5(l) = (a^l c - c^l a) (1 - (-1)^l),$$

$$a_6(l) = (a^{l+2} c^2 + c^{l+2} a^2) (1 + (-1)^l),$$

$$a_7(l) = (a^{l+2}c - c^{l+2}a)(1 - (-1)^l),$$

$$a_8(l) = (a^{l+2} + c^{l+2})(1 + (-1)^l),$$

$$a_9(l) = (a^{l+1} - c^{l+1})(1 - (-1)^l),$$

$$a_{10}(l) = (a^{l-1}c - c^{l-1}a)(1 + (-1)^l),$$

$$a_{11}(l) = (a^l + c^l)(1 + (-1)^l), \quad l \in N,$$

$$\alpha(t) = e^{-\kappa t} 1(t),$$

$$h_i(t) = \frac{1}{8} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \frac{\kappa^l (t - l\tau)^l}{l!} e^{-\kappa(t-l\tau)} 1(t - l\tau),$$

$$i = \overline{2, 9}, \quad 0 < t < (L+1)\tau,$$

$$h_i^{(1)}(t) = \frac{1}{8} \sum_{l=1}^L \frac{1}{2^l} a_i(l) \left[1 - \sum_{v=0}^{l-1} \frac{\kappa^v (t - l\tau)^v}{v!} e^{-\kappa(t-l\tau)} \right].$$

$$\cdot 1(t - l\tau), \quad i = 1, 2, 5, 10, \quad 0 < t < (L+1)\tau.$$

4. Conclusions

1. The exact expressions for the step responses of the forced synchronization system with delays, composed of n ($n \in N$) oscillators joined into a chain are obtained.
2. The obtained expressions can be applied to investigate the transient responses of the synchronization system, calculate statistical characteristics, examine behaviour of the system in the steady state.
3. The method of dynamic's investigation, used in the paper, can also be applied to other automatic control systems, described by the linear matrix differential equations of the first order with delayed argument.

References

- [1] **S. Bregni.** A Historical Perspective on Telecommunications Network Synchronization. *IEEE Communications Magazine*, June, 1998, 158-166.
- [2] **J. Rimas.** Investigation of the dynamics of mutually synchronized systems. *Radiotekhnika*, Vol.32, No.2, 1977, 3-9 (in Russian).
- [3] **J. Rimas.** On computing of arbitrary positive integer powers for one type of odd order tridiagonal matrices with zero row – 1. *Applied Mathematics and Computation*, 169, 2005, 1390 - 1394.
- [4] **P. Horn, Ch. Johnson.** Matrix Analysis. *Cambridge University Press*, Cambridge, 1986, 654.
- [5] **S. Peshkovskij.** Vytchistitelnyje primenenija mnogotchenov i riadov Tchebysheva. *Nauka, Maskva*, 1983, 383 (in Russian).

Received February 2006.

DOI: 10.5755/j01.itc.35.1.12038